

# **ACTIVE RFID**



- Instant reporting of detected Wavetrend active RFID tags
- User configurable tag data and read range filters
- Singular use or as part of multiple reader daisy chain network
- Easy remote configuration via the reader network
- Supports RS232, RS485 and USB connection
- Supports wide variety of antennas to achieve custom coverage areas
- Compatible with both L Series and L Series+

The RX210 reader detects and decodes RFID (radio frequency identification) signals from Wavetrend's range of active RFID tags. It can operate in rugged conditions at ultra long ranges, subject to the appropriate antenna being fitted to the unit. The data from detected tags is sent by the reader via RS485 / RS232 or USB to authorised corporate computing systems.

## **Typical Applications**

This reader is ideally suited for use in systems that track tagged assets such as containers, plant and machinery or high value assets, or for monitoring personnel in health and safety or security applications. The RX210 readers can be used to create RFID networks within buildings. For more robust and rigorous uses they can be deployed externally across large complexes, such as container ports, warehouses or external yards if suitably protected.

The tag data and reader status information is fed into the end-user application enabling complete management of all tagged assets and the automation of business decisions about them based on accurate and near real-time knowledge of their location and condition.

KEY FEATURES	BUSINESS BENEFITS
Up to 255 unique Receiver Addresses possible	Allows for multiple readers to be connected in a daisy-chain RS485 network
Remote readers are powered via standard CAT5 cable centralised or distributed PSU topology may be used.	Units can be powered over the network or individually depending on the clients requirements
Reader status indication by LED's at RJ45 connectors.	Provides activity and function diagnostics
Certified for FCC and ETSI	Can be deployed in all major countries
High RF long and short range sensitivity	High near field resolution < 0.5m
USB connection	Allows easy installation diagnostics and demonstrations
RF hardened Receiver	Maintains high performance in RF noisy backgrounds
Configurable protocol support for both L and L series Plus	Can read both L series and L series plus tags
Two modes of data transmission:  Hardware auto-polling: tag data provided automatically from Reader network  Software polling: tag data requested from each reader	<ul> <li>Hardware auto-polling allows for the continuous feed of tag data to the system in the fastest possible manner.</li> <li>Software poling allows for dynamic communication with</li> </ul>
individually by intelligent edge devices or host application.	each reader by software applications, instant notification of reader offline and customisation of reader polling order and frequency.

RFID | ACTIVATING YOUR BUSINESS

# **ACTIVE RFID**

## **Compatibility**

The RX210 is designed for use with the Wavetrend IPSU and RX211 access readers, these products can all be networked using standard cat 5 cabling. It may also be used as a direct replacement for an RX201, when used in the conjunction with the RX201 pin out adapter.

The RX210 can be configured to read both L series and L series tags simultaneously allowing the user to benefit from the added functionality of the L Series+ products whilst still supporting existing L Series tags.

## L Series+

L-Series+ offers a wide range of extra features including:

**Increased levels of security,** Encrypted air interface and secure concealed site code options

**Multiple classes,** allowing the user to select shorter messaging packets for high speed or high density application

**User definable data fields**, with up to 200 characters of user data to be stored on the tag

**Smart telemetry tag**, that alerts the user of out of bound temperature and humidity conditions and that logs the data

Greater selection of tag beacon rates allowing

## RX210 Accessories Antenna Ranges

AN100	1/4 Whip up to 50m
AN200	1/8 Stub- up to 20m
AN350	Circular patch up to 150m
AN400	Outdoor Whip up to 150m









AN100

**AN200** 

AN350

**AN400** 

\*Read ranges are affected by environmental conditions and site configurations and may not match those stated in this sheet. Read ranges will generally be greater outdoors than indoors. With specialist antennas, ranges in excess of 500m can be achieved.

## **Specifications**

### **Environmental**

- Operating temperature
- Storage temperature
- Humidity

### : -40°C to +85°C

- : -20°C to +70°C
- : 5% to 90% (non condensing)

#### **Physical**

- Size
- Weight (unit)
- Colour
- Material
- Connections

- : 105 mm x 58mm x 28mm
- : 118 grams
- : Aluminium Grey
- : Aluminium
- : 2 x RJ45 socket
- : 1 Mini USB type socket
- : 2.5mm Power socket

#### **Radio Frequency**

- Receive Frequency
- Modulation
- RF Input

- : 433.92 MHz
- : ASK
- : 50 Ohm BNC

#### **Electrical**

- Supply Voltage
- Max. current consumption
- : 7V ~ 16Vdc
- : 20 ma

#### **Protocol Specification**

- Standard Data Rate
- Interface

- : 9,600 ~ 115,200 (baud rate)
- : RJ45 connectors

# **Serial Networking hardware**

Completing the networking suite please for all power and access control requirements please refer to the RX211 and IPSU.







RX211

IPSU

RX201 -RX210 Adapter

## Ordering & Further Information

For more information on purchasing the RX210 please email the Wavetrend' Sales team:

### sales@wavetrend.net

For more information on Wavetrend<sup>®</sup> visit our website.

### IP Information

Wavetrend and the Wavetrend logo are either registered trademarks or trademarks of Wavetrend Technologies Limited in the United States and/or other countries. All other trademarks are the property of their respective owners. The product(s) described in this document are protected by various patents held by Wavetrend. Refer to the URL www.wavetrend.net/IPR for information on all patents and trademarks held, and for Wavetrend's Policy on Intellectual Property Rights.







